Vertiv[™] Liebert[®] GXE

Essential and Affordable UPS for High Performance Power Protection 6000 VA – 10000 VA, 230V, Rack/Tower Convertible



Overview



Vertiv[™] Liebert[®] GXE 6kVA in a flexible rack or tower mounting form factor

Liebert[®] GXE Features:

- High output power factor (1.0)
- Full-color graphic LCD
- High efficiency in online mode (up to 94%)
- ECO mode (up to 98% efficiency)
- Flexible rack/tower design
- Rack mounting kit included
- Extended runtime with up to 4 External Battery Cabinets (EBC)
- User replaceable internal UPS batteries
- Remote management capability with optional network management cards
- Automatic internal bypass
- Fast recharge time (3 hours @90%)
- Wide input frequency operation (40-70Hz) without any power derating
- Free UPS management software Vertiv[™] Power Insight and Vertiv[™] Power Assist

The Vertiv[™] Liebert[®] GXE UPS in an online double conversion solution which offers power protection in an affordable, efficient system with deployment and operation flexibility.

The unity output power factor (1.0) of the Liebert[®] GXE UPS enables continuous and reliable power to more connected devices, protecting them against many disturbances in the AC mains with the online double conversion technology.

The high efficiency in both line and ECO modes of operation for this already affordable UPS also drives energy and operational costs savings.

It provides flexibility for mounting in either tower position or inside a rack cabinet, together with the IT equipment critical for any application. Moreover, the capability to add external battery cabinets provides scalable runtime for those applications requiring even a longer period of backup in case of AC mains failures.

In addition to the extended runtime, having multiple monitoring options make this compact UPS ideal for delivering best-in-class power protection to equipment at the edge of networks or in remote sites.





Intuitive interface with detailed information and the ability to configure multiple parameters

What's In The Box

- Liebert GXE Unit
- Quick Installation Guide
- Safety Instructions
- Adjustable 4-post rack mounting kit
- Rack mounting ears/hardware
- Stabilizing feet for tower configuration

- USB type A to B cable (1.2 m)
- Free download <u>Vertiv[™] Power Assist</u> software for local UPS status and shutdown, or <u>Vertiv[™] Power Insight</u> for remote network management with the optional IS-UNITY network management card



Technical Specifications

| | GXE3-6000IRT4UXL | GXE3-10KIRT5UXL |
|---|---|---|
| Power Rating (VA/W) | 6000VA / 6000W | 10000VA / 10000W |
| Form Factor | Rack / Tower (4U) | Rack / Tower (5U) |
| Dimensions, mm | | |
| Jnit (W x D x H) | 430 x 750 x 173 | 430 x 700 x 217 |
| Shipping (W x D x H) | 600 x 850 x 480 | 600 x 800 x 530 |
| Weight, kg | | |
| Jnit | 70 | 80 |
| Shipping | 92 | 102 |
| nput AC Parameters | | |
| foltage Range Without Battery Operation 230V default, derating applies)* | 100 - 288 | 100 - 288 |
| /oltage Range Without Battery Operation 230V default, 100% load) | 176 - 288 | 178 - 288 |
| requency Range (Hz, autosensing) | 40 - 70 | 40 - 70 |
| nput Wiring | Hardwired (terminals L-N-G) | Hardwired (terminals L-N-G) |
| Surge Protetion (J) | 600 | 600 |
| Dutput AC Parameters | | |
| Dutput Voltage | 220/230 (default) /240 | 220/230 (default) /240 |
| Vaveform | Pure Sine Wave | Pure Sine Wave |
| Output Overload (AC Mode) | 105% - 125% @ 5 min - 126% - 150% @ 1 min > 150% @ 200 ms | 105% - 125% @ 5 min - 125% - 150% @ 1 min > 150% @ 200 ms |
| utput wiring | Hardwired (terminals L-N-G) | Hardwired (terminals L-N-G) |
| fficiency (online mode, max.) | 94% | 94% |
| fficiency (ECO mode, max.) | 98% | 98% |
| Battery | | |
| уре | Valve-regulated, non-spillable, lead-acid | Valve-regulated, non-spillable, lead-acid |
| echarge Time (internal batteries, typical) | 3 hr @ 90% | 3 hr @ 90% |
| ackup Time (100% load, minutes) | 5 | 3.5 |
| ackup Time (50% load, minutes) | 14 | 9 |
| Comaptible External Battery Cabinet | GXE3-EBC192VRT2U | GXE3-EBC240VRT3U |
| nvironmental | | |
| perating Temperature (°C) | 0 to 40°C | 0 to 40°C |
| torage Temperature (°C, without battery inside) | -20°C to +70°C | -20°C to +70°C |
| elative Humidity (operation, non-condensing) | 5% to 95% | 5% to 95% |
| Operating Altitude (m), without derating (**) | 2000 | 2000 |
| udible Noise (line mode) | <55dBA | <58dBA |
| Agency | | |
| Compliance | CE, CB Report, EAC, UKCA, Morocco, RCM | CE, CB Report, EAC, UKCA, Morocco, RCM |
| Safety | IEC/EN 62040-1 | IEC/EN 62040-1 |
| ransportation | ISTA 3E | ISTA 3E |
| nvironmental | RoHS, REACH, WEEE | RoHS, REACH, WEEE |
| communications and Management | | |
| lot for optional cards | Yes | Yes |
| ommunication port | USB | USB |
| mergency Power Off (EPO) | Yes | Yes |
| Varranty | | 100 |
| Varranty (electronics and batteries) | 2 years | 2 years |

(*) Note: Specific conditions or power derating applies. (**) Note: Up to 3000 m with power derating.

External Battery Cabinets

| Dimensions, mm | GXE3-EBC192VRT2U | GXE3-EBC240VRT3U |
|----------------------|-----------------------------------|-----------------------------------|
| Unit (W x D x H) | 430 x 765 x 85 | 430 x 645 x 130 |
| Shipping (W x D x H) | 600 x 850 x 405 | 600 x 800 x 450 |
| Weight, kg | | |
| Unit | 58.4 | 66.9 |
| Shipping | 78 | 85 |
| Agency | | |
| Compliance | CE, CB Report, EAC, UKCA, Morocco | CE, CB Report, EAC, UKCA, Morocco |

Vertiv.com | Vertiv Headquarters, 505 N. Cleveland Ave., Westerville, Ohio, 43082, USA

© 2023 Vertiv Group Corp. All rights reserved. Vertiv³⁷ and the Vertiv logo are trademarks or registered trademarks of Vertiv Group Corp. All other names and logos referred to are trade names, trademarks or registered trademarks of their respective owners. While every precaution has been taken to ensure accuracy and completeness here, Vertiv Group Corp. assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications, rebates and other promotional offers are subject to change at Vertiv's sole discretion upon notice.